

Introducing LED Tape Light

120V RGB

Features

- High voltage input, low current, reaches 50FT continuously running, easy to install and maintain.
- Using double 18φ0.18 copper wire as lead wire, low voltage dropping and heat.
- Using SMD 5050 RGB as light source, high-transmitting PVC cover, high efficiency and brightness.
- Double PVC encapsulated, security and reliable.
- CE, Rohs and ETL listed/CE, Rohs and ETL



Specification

Catalog Number	Size (mm)	Reel Length (FT)	Input Voltage (V)	Lamp Watt (W/FT)	Efficiency (LM/W)	Lumen Output (LM/FT)	CCT (K)	CRI	Life Time (HRS)	Max Run
LS-TPL2.13W/120V/10m/RGB-R	16*7.5	32.8	120VAC	2.13	25	55	RGB	--	50,000	164
LS-TPL2.13W/120V/50m/RGB-R	16*7.5	164	120VAC	2.13	25	55	RGB	--	50,000	164
LS-TPPC/120V-RGB	The Power Cord for the 120VAC RGB Color tape light, max run is 164FT, with Plug.									
LS-TP/EC2	End Cap for 0.63"*0.3" 120VAC RGB Tape Light.									

**R= Suitable for outdoor.

**The controller is included with the power cord.

